

Aspera

HIGH PERFORMANCE TWO WAY RADIO

V7

- Voice Scrambler
- 360° Microphone
- Comander
- Power Saving Function
- Dust & Splash Proof
- Alarm/Scanning/Hi-Low Power Selection
- VOX Functions



CTCSS/DCS
16 channels

VHF/UHF FM Transceiver

V7

VHF/UHF FM Transceiver

Aspera

HIGH PERFORMANCE TWO WAY RADIO

Main Functions

- 16 channels
- PC Programmable
- VOX functions
- CTCSS/DCS
- English voice prompt
- Power saving function
- High-low power selective
- Scanning function
- Scrambler
- COMP function
- Wide/narrow bandwidth selective
- End tone elimination
- Emergency alarm

General

Transmitter

Receiver

Frequency range	VHF 136-174MHz	UHF 350-390MHz	RF Output power	VHF-5W UHF-4W	Receiving sensitivity	<0.2μV
Operating temperature	-20℃~+50℃		Frequency stability	± 2.5ppm	Audio distortion	≤5%
Operating voltage	DC 7.2V		Modulation Limiting	≤2.5KHz	Audio response	+2dB~-10dB
Operate mode	Simplex or Semi-duplex		Audio distortion	≤5%	Co-channel suppression	≥-8dB
Antenna impedance	50Ω		Modulation character	+3dB~-3dB	Adjacent Ch. selectivity	≥ 55dB
Weight	190g(Include battery & antenna)		Adjacent Ch. power	≥ 65dB	Intermodulation rejection	≥ 55dB
Dimensions (WxHxD)	116x57x34mm		Spurious radiation	≤7.5μW	Spurious response	≥ 65dB
Battery Cell	2000mAh Li-ion		Occupied bandwidth	≤16KHz	Blocking	≥ 85dB

Standard Accessories



Optional Accessories



More accessories please refer to our website.



Approved by GB/T19001-2008 ISO9001:2008
ID: 01609Q21255R0M